

Saturn SX360 IP Camera Quick Guide

The Quick Guide is for quick installing and connecting the Saturn 360 IP Camera. For more details, please refer to the User's Manual of the camera in the supplied CD.

Camera's Connectors (Indoor Only)

No.	Definition
1	
2	Network and PoE connections
3	microSD card slot
4	Alarm In + and Alarm In -
5	Alarm & Audio I/O

No.	Connector	Pin	Definition	Remarks
3	Alarm I/O (4-Pin Terminal Block)	1	Alarm In -	Alarm connection
		2	Alarm In +	
3	Alarm Out -			
4	Alarm Out +			
4	GND	-	GND	Ground connection
5	RJ-45	-	For network and PoE connections	
-	microSD Card Slot	-	Refer to the Default Button in the table under section Camera's Connectors (Indoor Only) .	
-	Default Button	-	Refer to the microSD Card Slot in the table under section Camera's Connectors (Indoor Only) .	

NOTE: It is not recommended to record with the microSD card for 24/7 continuously, as it may not be able to support long term continuous data read/write. Please contact the manufacturer of the microSD card for information regarding the reliability and the life expectancy.

Camera Cabling

Please follow the instructions below for cable connections.

Power Connection

Please use a DC 12V power adaptor and plug it to the camera and the power outlet. Alternatively, users can use an Ethernet cable and connect it to the RJ-45 connector of the camera and a Power Sourcing Equipment (PSE) switch.


NOTE: If PoE is used, make sure PSE is in used in the network.

Ethernet Cable Connection

Connect one end of the Ethernet cable to the RJ-45 connector of the camera, and plug the other end of the cable to the network switch or PC.


NOTE: In some cases, Ethernet crossover cable might be needed when connecting the camera directly to the PC.

NOTE: Check the status of the link indicator and activity indicator LEDs. If the LEDs are unlit, please check the LAN connection.



Green Link Light indicates good network connection.
Orange Activity Light flashes for network activity indication.

Function Cable (Outdoor Only)



No.	Connector	Pin	Definition	Remarks
1	Audio I/O	Pink	Audio In	Two-way audio transmission
		Green	Audio Out	
2	Power (DC 12V) (2-Pin Terminal Block)	Black	DC 12V -	Power connection
		Red	DC 12V +	
3	Alarm I/O (4-Pin Terminal Block)	1	Alarm In -	Alarm connection
		2	Alarm In +	
		3	Alarm Out -	
		4	Alarm Out +	
4	GND	-	GND	Ground connection
5	RJ-45	-	For network and PoE connections	
-	microSD Card Slot	-	Refer to the Default Button in the table under section Camera's Connectors (Indoor Only) .	
-	Default Button	-	Refer to the microSD Card Slot in the table under section Camera's Connectors (Indoor Only) .	

Before Login to the Camera

A client program will be automatically installed to the PC when connecting to the camera. Before logging in to the camera, please ensure downloading the ActiveX control is allowed by either changing the ActiveX controls and plug-ins or setting Internet's security level to default. For further details, please refer to the User's Manual in the supplied CD.

ActiveX Controls and Plug-ins Settings	Internet Security Level
Step 1: Start the Internet Explorer (IE). Step 2: Select <Tools> from the main menu of the browser. Then click on <Internet Options>. Step 3: Click on the <Security> tab and select <Internet>, and click on <Custom level> to change ActiveX settings. Step 4: Set "ActiveX controls and plug-ins" items to <Prompt> or <Enable>.	Step 1: Start the Internet Explorer (IE). Step 2: Select <Tools> from the main menu of the browser. Then click on <Internet Options>. Step 3: Click on the <Security> tab and select <Internet>. Step 4: Down the page, click <Default Level> and click on <OK> to confirm the setting. Close the browser window, and open a new one later for accessing the IP camera.

Camera Login

The default IP address of the camera is: **192.168.0.250**. Therefore, to access the camera for the first time, please set the IP address of the PC as: 192.168.0.XXX; for example:

IP Address: 192.168.0.100

Subnet Mask: 255.255.255.0

Login ID and Password

- Key in the camera's IP address in the URL bar of the web browser window and hit on "Enter".
- Enter the default username (**Admin**) and password (**1234**) in the prompt request dialogue. Note that username is case sensitive.

Install the ActiveX Control

- After connecting to the camera, the request for installing the ActiveX control will appear just below the URL bar.
- Right click on the information bar, and then click on <Install ActiveX Control...> to permit ActiveX control installation.



- In the pop-up security warning window, click on <Install> to start downloading Viewer software on the PC.
- Click on <Finish> after Viewer installation is completed.

Browser-based Viewer

The main page of the IP camera user interface is shown as the figure below. Please note that function buttons will vary depending on the camera model.



Saturn SX360 Fisheye IP Camera Quick Guide