



USB-LON Adapter for System-X Configuration



The USB-LON Adapter is used for connecting a PC to the LonWorks control bus of System-X when configuring a system. Because it has a USB interface towards the PC, it can be used with both laptop and desktop PCs.

The USB-LON adapter receives its power from the USB connection and therefore does not require any external power supply

Once the configuration of the System-X is completed, the USB-LON adapter can be removed from the system.

The USB-LON Adapter is supplied with a USB A/B cable, a CD with the necessary drivers and an installation instruction.



The USB-LON Adapter is a small compact unit

Specifications

USB Interface	
Interface type	USB 1.1
Connector type	USB B
LED	Status LED
LONWORKS interfaces	
Interface type	LONWORKS 78 kbit/s, FTT-10A
Connector type	RJ-45 and 3-pin screw type (0.5 to 2.5 mm ²)
Display / operation	Service LED and push-button
Environmental Specifications, all products	
Power supply	5 VDC from USB port
Input current	100 mA max.
Operating temperature	0°C to +50°C
Humidity	DIN 40 040, class F
Dimensions (W x H x D)	128 x 23 x 71 mm
EMC	EN 50081-1, EN 50081-2



THE ONE TO WATCH

LONWORKS, also known as LON, is a communication network. As opposed to TCP/IP (Ethernet), LONWORKS is designed for control applications such as building automation, transportation, home automation, security and other systems. For more information about LONWORKS, please refer to www.echelon.com.

LON and LONWORKS are trademarks of Echelon Corporation.

Denmark Head Office

Ernitec A/S
Hørkær 24
2730 Herlev
Denmark
Phone: +45 44 50 33 00
Fax: +45 44 50 33 33
ernitec@ernitec.dk
www.ernitec.com

French Branch Office

Ernitec France
N° 29 Parc Club du
Millenaire
1025 Rue Henri Becquerel
34036 Montpellier cedex 1
France
Phone: 04 67 15 10 15
Fax: 04 67 64 01 81
ernitec@ernitec.fr
www.ernitec.com

German Branch Office

Ernitec GmbH
Stormarnring 28
22145 Stapelfeld
Germany
Phone: 040 67 56 25 0
Fax: 040 67 56 25 25
ernitec@aol.com
www.ernitec.com

UK Branch Office

Ernitec UK
Gerrard House
Worthing Road
East Preston
West Sussex BN16 1AW
England
Phone: 01903 77 27 27
Fax: 01903 77 27 07
sally@ernitec.co.uk
www.ernitec.com

Middle East Office

Ernitec ME
Hamra - Makdesi Street
Younis Center - 5th floor
Office no. 503
P.O.Box: 113/5721
Beirut
Lebanon
Phone: +961 1 751 796
Fax: +961 1 751 795
Malek_kabrit@ernitecme.com
www.ernitecme.com